Serial Number:	Date:
Tech:	

LASER INTERFEROMETER GRAVITATIONAL WAVE OBSERVATORY

-LIGO-

CALIFORNIA INSTITUTE OF TECHNOLOGY

MASSACHUSETTS INSTITUTE OF TECHNOLOGY

Document Type	DCC Number	July 5, 2002		
	T020082-A-C			
8 Channel Anti-Image Filter Board Test Plan				
J. Heefner				

Distribution of this draft: This is an internal working note of the LIGO Laboratory

California Institute of Technology LIGO Project – MS 18-33 Pasadena, CA 91125

Phone (626) 395-2129 Fax (626) 304-9834 E-mail: info@ligo.caltech.edu Massachusetts Institute of Technology LIGO Project – MS 20B-145 Cambridge, MA 01239 Phone (617) 253-4824

Fax (617) 253-7014 E-mail: info@ligo.mit.edu

www: http://www.ligo.caltech.edu/

Serial Number:	Date:
Гесh:	
4 1 4 1 4!	

1 Introduction

The tests described below are required to verify the correct operation of the 8 Channel Anti-Image Filter Board (D000186, Rev B). The transfer function of this board is a 7 pole, 6 zero, 4 dB ripple, 60 dB attenuation , 7570 Hz elliptic low pass filter. Note that this board is different from D000186, Rev A which uses discrete op amp stages to produce an elliptic response. The Rev A version of the board requires a different test plan.

2 Test Equipment

Dynamic Signal Analyzer Oscilloscope Power supplies

3 Tests

3.1 Input Power

Record the input voltage and current in the table below. Values should be +/-20mA of the nominal values.

Supply	Nominal Current	Actual	Pass/Fail
+15 V	0.25 A		
-15 V	0.25 A		


3.2 Filter Response

The nominal response of each channel is a 4 dB ripple, 60 dB attenuation, 7 pole, 6 zero elliptic low pass. The cutoff frequency is 7570 Hz and response zeros are located at 16384 Hz and 37.5 KHz. Using the dynamic signal analyzer, verify and record the response of each channel in the table below. The stopband is defined as frequencies above 16KHz.

Chan	Input/	Passband	Stopband	Fcutoff	$\mathbf{F_{zero}} =$	$\mathbf{F}_{\mathbf{zero}} =$	Pass/
	Output	Ripple	Atten >	=	16384	37.5	Fail
		<4dB?	60dB	7570Hz	Hz	KHz	
				+/-	+/-	+/-	
				500Hz?	0.5KHz	0.5KHz	
					?	?	
1	J1-39 / J7-1						
2	J1-35 / J7-3						
3	J1-31 / J7-5						
4	J1-27 / J7-7						
5	J1-23 / J8-1						
6	J1-19 / J8-3						
7	J1-15 / J8-5						
8	J1-11 / J8-7						

A plot of the nominal transfer function is shown in the figure below.

Serial Number:	Date:
Tech:	



3.3 Monitor Operation

Verify the correct functioning of the front panel and EPICS monitors for each channel using a 100Hz, $1V_{p-p}$ sine wave and an oscilloscope.

Channel	EPICS	EPICS	FP Monitor	FP	Pass/Fail
/ Input	Monitor	Monitor =		Monitor =	
		1Vp-p,		1Vp-p,	
		100 Hz?		1KHz?	
1 / J1-39	P1-1A		J3A		
2 / J1-35	P1-2A		J3B		
3 / J1-31	P1-3A		J4A		
4 / J1-27	P1-4A		J4B		
5 / J1-23	P1-5A		J5A		
6 / J1-19	P1-6A		J5B		
7 / J1-15	P1-7A		J6A		
8 / J1-11	P1-8A		J6B		

Serial Number:	Date:
Tech:	

3.4 Output Noise

The output noise of each channel should be less than $500 \text{nV/}\sqrt{\text{Hz}}$ for 5 Hz < freq < 10 KHz, neglecting line related peaks related to measurement. For ease of connection, the front panel monitors are used for these tests, but they provide a reasonable measurement of the channel output noise.

Channel / Input	Output Monitor	Noise Out < 500nV/√Hz ?	Pass/Fail
1 / J1-39	J3A		
2 / J1-35	J3B		
3 / J1-31	J4A		
4 / J1-27	J4B		
5 / J1-23	J5A		
6 / J1-19	J5B		
7 / J1-15	J6A		
8 / J1-11	J6B		