



LASER INTERFEROMETER GRAVITATIONAL WAVE OBSERVATORY

*LIGO Laboratory / LIGO Scientific Collaboration*

LIGO-E2200008-v1

*Advanced LIGO*

6 January 2022

---

Test Procedure for Slow Controls Concentrator Auxiliary 10

---

Daniel Sigg

Distribution of this document:  
LIGO Scientific Collaboration

This is an internal working note  
of the LIGO Laboratory.

**California Institute of Technology**  
**LIGO Project – MS 18-34**  
**1200 E. California Blvd.**  
**Pasadena, CA 91125**  
Phone (626) 395-2129  
Fax (626) 304-9834  
E-mail: [info@ligo.caltech.edu](mailto:info@ligo.caltech.edu)

**Massachusetts Institute of Technology**  
**LIGO Project – NW22-295**  
**185 Albany St**  
**Cambridge, MA 02139**  
Phone (617) 253-4824  
Fax (617) 253-7014  
E-mail: [info@ligo.mit.edu](mailto:info@ligo.mit.edu)

**LIGO Hanford Observatory**  
**P.O. Box 1970**  
**Richland WA 99352**  
Phone 509-372-8106  
Fax 509-372-8137

**LIGO Livingston Observatory**  
**P.O. Box 940**  
**Livingston, LA 70754**  
Phone 225-686-3100  
Fax 225-686-7189

<http://www.ligo.caltech.edu/>

## 1 Overview

The slow controls concentrator auxiliary 10 supports 2 DC photodiode amplifiers, and 4 photodiodes interfaces.

## 2 Test Equipment

- Multimeter, scope and signal generator.
- Second slow controls concentrator auxiliary 10 ([D2200010-v1](#)).  
Replace the 3 front-panel breakout boards with quad TNC breakouts.
- 2 test cables DB9 to 4xBNC ([D1102414-v1](#)).
- DC power supplies.

## 3 Documentation

- Schematics - [D2200010-v1](#)

## 4 Tests

Power up the measurement equipment and open the lid of the DUT. Connect a DB37 cable (male-male) between the DUT and the second slow controls concentrator. Connect the test cables to “Photodiode DC 1-4 IN” and “Photodiode DC 1-4 OUT”.

### 4.1 Power

Check the voltages on the concentrator power board. The voltage should be within 5% of nominal. Test that the OK signal is a TTL low (<0.8V).

TP6 (+5V)\_\_\_\_\_

TP8 (+15V)\_\_\_\_\_

TP3 (-15V)\_\_\_\_\_

TP9 (OK) \_\_\_\_\_

### 4.2 LED

Check that the LED on the front panel and the 2 LEDs on the rear panel are lit.

Front panel LED\_\_\_\_\_

Rear panel LEDs\_\_\_\_\_

### 4.3 Testing

Apply a 1kHz sine wave to each the BNCs of the first test cable while measuring the response with a scope on the second test cable, at the front panel BNCs of the DUT (Photodiode Monitors) and at the front panel BNCs of the second concentrator (Photodiode Monitors).

Cable 1	Pass/Fail				
	Cable 2	DUT		2 <sup>nd</sup> concentrator	
		PDMon	PDMon+4	PDMon	PDMon+4
BNC 1					
BNC 2					
BNC 3					
BNC 4					

Move on of the test cables to the PD Amp DC 1-2 connector. Measure the voltage of the photodiode amplifier monitors at the DUT at the second chassis and at the rear cable (should be close to zero). The quad TNC breakouts of the second chassis have the connectors assigned as Gain 1 input, Gain 2 input, Monitor 1, Monitor 2, respectively.

Signal	Voltage at DUT	Voltage at 2 <sup>nd</sup> unit	Cable
Photodiode amplifier monitor 1			
Photodiode amplifier monitor 2			

Clip a 100 k $\Omega$  resistor to the TNC PD input of each DC photodiode amplifier channel in turn. Measure the voltage of the photodiode amplifier monitors at the DUT at the second chassis and at the rear cable. Make one measurement at this gain (voltage should be 100mV).

Signal	Voltage at DUT	Voltage at 2 <sup>nd</sup> unit	Cable
Photodiode amplifier monitor 1			
Photodiode amplifier monitor 2			

Now ground the center pin of the corresponding gain input and measure again (should be 315mV).

Signal	Voltage at DUT	Voltage at 2 <sup>nd</sup> unit	Cable
Photodiode amplifier monitor 1			
Photodiode amplifier monitor 2			

Ground both the center pin and the outer shell to ground, measure again (should be 1.00V).

Signal	Voltage at DUT	Voltage at 2 <sup>nd</sup> unit	Cable
Photodiode amplifier monitor 1			
Photodiode amplifier monitor 2			

Ground the outer shell to ground, measure again (should be 3.15V).

Signal	Voltage at DUT	Voltage at 2 <sup>nd</sup> unit	Cable
Photodiode amplifier monitor 1			
Photodiode amplifier monitor 2			